

ART.	kVA	kVA	U <sub>1</sub> /Freq Volt/Hz	V <sub>2d</sub> Volt				I <sub>2</sub> 20%	I <sub>2</sub> 50%
	20%	50%		1	2	3	4	kA	kA
MFT-010-2-2-10000-00	15	10	500/2÷10k	4.0	5.0	-	-	3	2
MFT-025-1-2-10000-00	25	16	500/2÷10k	11.5	-	-	-	2.17	1.37
MFT-025-1-2-10000-01	25	16	275/2÷10k	11.5	-	-	-	2.17	1.37
MFT-030-1-2-10000-00	48	30	500/2÷10k	11.5	-	-	-	4.12	2.61
MFT-030-1-2-10000-01	25	16	500/2÷10k	6.0	-	-	-	4.12	2.61
MFT-030-1-2-10000-02	28	18	500/2÷10k	6.8	-	-	-	4.12	2.61
MFT-030-1-2-10000-03	48	30	275/2÷10k	11.5	-	-	-	4.12	2.61
MFT-100-1-2-10000-00	-	100	530/10k	11.5	-	-	-	13.38	8.46
MFT-040-2-2-01000-01	-	40	500/1k	5.3	6.3	-	-	9	6
MFT-060-2-2-01000-03	-	60	500/1k	5.9	6.7	-	-	13.5	8.9
MFT-080-2-2-01000-01	-	80	500/1k	6.8	7.6	-	-	16.3	10.3
MFT-100-2-4-01000-02	-	112	500/1k	8.6	11.5	-	-	15.44	9.76
MFT-150-2-4-01000-01	-	165	500/1k	7.3	10.3	-	-	25	16
MFT-180-2-4-01000-05	-	190	500/1k	9.5	12.3	-	-	24.5	15.5
MFT-180-2-4-01000-06	-	190	500/1k	9.5	12.3	-	-	24.5	15.5
MFT-180-4-6-01000-07	-	190	500/1k	8.1	8.8	9.5	10.4	28.6	18
MFT-180-2-4-01000-08	-	190	500/1k	9.5	12.3	-	-	24.5	15.5
MFT-250-2-4-01000-02	-	286	500/1k	11.6	13.6	-	-	33.4	21.1
MFT-250-2-4-01000-03	-	286	500/1k	11.6	13.6	-	-	33.4	21.1
MFT-250-3-4-01000-04	-	256	500/1k	9.5	10.6	12.1	-	33.5	21.2
MFT-250-3-4-01000-05	-	256	500/1k	9.5	10.6	12.1	-	33.5	21.2
MFT-300-2-8-01000-03	-	300	500/1k	7.8	10.0	-	-	47	30
MFT-300-2-6-01000-04	-	300	500/1k	9.6	11.8	-	-	40	25